

# Infiniium UXR-B Series Oscilloscopes

The most advanced Real-Time Oscilloscope on the planet. Now experience a whole new level of performance with new Infiniium UXR-B Series.

## Introduction

The Infiniium UXR-Series oscilloscopes deliver world-leading performance, ultra-low noise, and high signal fidelity for engineers and scientists to truly see and understand the fastest phenomena. The new UXR-B also comes with more memory. With standard 500Mpts memory, you can capture 2.5 times longer waveform to do analysis. Wider DDC and RTSA bandwidth can help you do the analysis faster and help you debug your wireless signal. For high-speed digital design, the InfiniiSim Basic de-embedding and PrecisionCable, PrecisionProbe now standard to help you remove channel loss.



# Table of Contents

|   |    |
|---|----|
| Introduction and Model Overview .....   | 2  |
| Vertical System Specifications - 3.5 mm Input Models .....                          | 4  |
| Vertical System Specifications – 1mm & 1.85 mm Input Models.....                    | 5  |
| Vertical System – Performance Characteristics by Model - 3.5 mm Input Models .....  | 6  |
| Vertical System – Performance Characteristics by Model - 1.85 mm Input Models.....  | 6  |
| Vertical System – Performance Characteristics by Model - 1 mm Input AP Models ..... | 7  |
| Vertical System – Performance Characteristics by Model - 1 mm Input Models.....     | 7  |
| RMS Noise Floor – Performance Characteristics (Measured).....                       | 8  |
| Vertical System – Performance Measurements – 1 mm & 1.85 mm Input Models .....      | 9  |
| Horizontal System – Performance Characteristics .....                               | 11 |
| DDC and Frequency Extension Option – Performance Characteristics .....              | 13 |
| Real Time Spectrum Analysis.....  | 14 |
| Acquisition System – Performance Characteristics .....                              | 15 |
| Trigger System – Performance Characteristics .....                                  | 16 |
| Measurements and Math .....   | 18 |
| Platform Characteristics .....  | 20 |
| General Characteristics.....  | 22 |
| Definitions.....  | 23 |
| Confidently Covered by Keysight Services .....                                      | 24 |
| More Information .....  | 25 |

**NOTE:**

For a description of key features, see the [Infiniium UXR-B Series Oscilloscopes Technical Overview](#).

For ordering information, see the [Infiniium UXR-B Series Oscilloscopes Configuration Guide](#).

# Introduction and Model Overview

**The UXR has more accurate analysis.** Up to four channels of simultaneous 110 GHz of bandwidth, each concurrently sampling at a staggering 256 GSa/s with 10 bits of high-definition analog to digital converter (ADC) resolution.

**The UXR runs faster.** Up to 100x faster performance for some measurements – enabled by a powerful new measurement acceleration ASIC and memory controller capable of 5 trillion integer operations per second (IOPS).

**The UXR is fully upgradeable.** The Infiniium UXR-Series is scalable – you can easily upgrade the bandwidth, memory, channel count, and software capabilities to meet your future needs.

The UXR is available in three models based on bandwidth, sample rate and input connector size. Infiniium UXR-Series models offer bandwidths from 5 GHz to 110 GHz with various 1-channel, 2-channel, or 4-channel configurations available. The 3.5mm models are equipped with Keysight AutoProbe II interfaces while 1mm and 1.85 mm models incorporate an advanced high-performance high-bandwidth Keysight AutoProbe III interface.



1 mm input models



1.85 mm input models



3.5 mm input models

| Model     | 4-Channel              | 2-channel | Bandwidth (maximum) | Connector | Power required                              |   | Sample rate (maximum) |
|-----------|------------------------|-----------|---------------------|-----------|---|---|-----------------------|
|           |                        |           |                     |           | 4-channel                                   | 2-channel                                   |                       |
| UXR1104B  | UXR1102B               |           | 110 GHz             | 1 mm      | 200 to 240 V <sub>ac</sub><br>2615 VA(Max)  | 110 to 240 V <sub>ac</sub><br>1350 VA (Max) | 256 GSa/s             |
| UXR1004B  | UXR1002B               |           | 100 GHz             |           |   |   |                       |
| UXR0804B  | UXR0802B               |           | 80 GHz              |           |   |   |                       |
| UXR0704BP | UXR0702BP              |           | 70 GHz              |           |   |   |                       |
| UXR0594BP | UXR0592BP              |           | 59 GHz              |           |   |   |                       |
| UXR0404BP | UXR0402BP              |           | 40 GHz              |           |   |   |                       |
| UXR0254BP | UXR0252BP              |           | 25 GHz              |           |   |   |                       |
| N/A       | UXR0051BP <sup>1</sup> |           | 5 GHz               | 1.85 mm   |   |   |                       |
| UXR0704B  | UXR0702B               |           | 70 GHz              |           |   |   |                       |
| UXR0594B  | UXR0592B               |           | 59 GHz              |           |   |   |                       |
| UXR0504B  | UXR0502B               |           | 50 GHz              |           |   |   |                       |
| UXR0404B  | UXR0402B               |           | 40 GHz              | 3.5 mm    | 100 to 240 V <sub>ac</sub><br>1350 VA (Max) | N/A   | 128 GSa/s             |
| UXR0334B  |                        |           | 33 GHz              |           |   |   |                       |
| UXR0254B  |                        |           | 25 GHz              |           |   |   |                       |
| UXR0204B  | N/A                    |           | 20 GHz              |           |   |   |                       |
| UXR0164B  |                        |           | 16 GHz              |           |   |   |                       |
| UXR0134B  |                        |           | 13 GHz              |           |   |   |                       |
| UXR0104B  |                        |           | 10 GHz              |           |   |   |                       |

1. The UXR0051BP includes two channels, but only one channel is licensed for use. The 2nd channel may be activated with purchase of an upgrade license – N2166A Upgrade 1 channel UXR0051BP to 2 channel UXR0254BP.

# Vertical System Specifications - 3.5 mm Input Models

| Specification   | 3.5 mm input models  |   |
|---|--|---|
| Sample rate per channel                               | 128 GSa/s (configurable in powers of two)  |   |
| Displayed input sensitivity <sup>1</sup>              | 1 mV/div to 1 V/div  |   |
| Hardware sensitivity <sup>1</sup>                     | 32 mV full scale to 8.0 V full scale   |   |
| Vertical resolution <sup>1,3</sup>                    | 10 bits, ≥ 14 bits with averaging  |   |
| DC gain accuracy <sup>1,2,3,*</sup>                   | ± 1.5% of full scale (typical: ±1% of full scale ≤ 10 mV/div, ±0.5% of full scale > 10 mV/div)   |   |
| DC voltage accuracy<br>Dual cursor:<br>Single cursor: | ± [(DC gain accuracy) + (resolution)]<br>± [(DC gain accuracy) + (offset accuracy) + (resolution/2)]   |   |
| Maximum input voltage                                 | ± 8 divisions from center screen (Absolute max ± 6.5 V)  |   |
| Input range   | ± 4 divisions from center screen   |   |
| Maximum input power                                   | +6 dB (twice the amplitude) at all ranges (+16 dBm at maximum range)   |   |
| Channel to channel isolation                          | Channel to channel (with equal V/div settings): 1-3, 1-4, 2-3, and 2-4: 60 dB<br>Channel to Channel (with equal V/div settings): 1-2, 3-4: 40 dB                   |   |
| Offset range  | <b>Vertical sensitivity</b><br>1 mV/div to 54 mV/div<br>55 mV/div to 93 mV/div<br>94 mV/div to 172 mV/div<br>173 mV/div to 306 mV/div<br>307 mV/div to 1000 mV/div | <b>Available offset</b><br>± 0.40 V<br>± 0.70 V<br>± 1.25 V<br>± 2.25 V<br>± 4.00 V |
| Offset accuracy <sup>1,2,3,*</sup>                    | ±1% of channel offset + 1% of full scale   |   |
| Offset accuracy (typical)                             | ±1% of channel offset + 0.5% of full scale   |   |
| Amplitude flatness <sup>4</sup>                       | Any frequency ≤ 33 GHz:<br>< 0.3 dB within any 500MHz span<br>< 0.5 dB within any 10GHz span   |   |
| Phase flatness <sup>5</sup>                           | Any frequency ≤ 33 GHz:<br>< 1 degree within any 500MHz span<br>< 2 degrees within any 10GHz span  |   |

1. Full scale is defined as 8 vertical divisions. Magnification is used below 4 mV/div. Below 4 mV/div, full scale is defined as 32 mV. The major scale settings are 1 mV/div, 2 mV/div, 5 mV/div, 10 mV/div, 20 mV/div, 50 mV/div, 100 mV/div, 200 mV/div, 500 mV/div and 1V/div. Magnification major scales of 1mV/div, 2mV/div & 5mV/div are not warranted for Offset Accuracy & DC Gain Accuracy.

2. Input impedance is valid when V/div scaling is adjusted to show all waveform vertical values within scope display.

3. Vertical resolution for 10 bits = 0.1% of full scale, for 14 bits = 0.006% of full scale.

4. Measured result using N2127A as reference. Maximum deviation from average in a span.

5. Measured result using N2127A as reference. Maximum deviation from best-fit line (degrees) in a span.

**\*Denotes warranted specifications, all others are typical. Valid after 30-minute warm up period and ±5 °C from oscilloscope firmware calibration temperature.**

# Vertical System Specifications – 1mm & 1.85 mm Input Models

| Specification                            | 1.85 mm & 1 mm input models  |                         |
|--|--|-------------------------|
| Sample rate per channel                  | 256 GSa/s (configurable in powers of two)                            |                         |
| Displayed input sensitivity <sup>1</sup> | 1 mV/div to 500 mV/div   |                         |
| Hardware sensitivity <sup>1</sup>        | 60 mV full scale to 4.0 V full scale                                 |                         |
| Vertical resolution <sup>1,3</sup>       | 10 bits, ≥ 14 bits with averaging                                    |                         |
| DC gain accuracy <sup>1,2,3,*</sup>      | ± 2% of full scale (typical: ±1% of full scale)                      |                         |
| DC voltage accuracy                      |  |                         |
| Dual cursor:                             | ± [(DC gain accuracy) + (resolution)]                                |                         |
| Single cursor:                           | ± [(DC gain accuracy) + (offset accuracy) + (resolution/2)]          |                         |
| Maximum input voltage                    | ± 8 divisions from center screen (Absolute max ± 4V)                 |                         |
| Input range                              | ± 4 divisions from center screen                                     |                         |
| Maximum input power                      | +6 dB (twice the amplitude) at all ranges (+16 dBm at maximum range) |                         |
| Channel to channel isolation             | 60 dB  |                         |
| Offset range                             | <b>Vertical sensitivity</b>  | <b>Available offset</b> |
|  | 1 mV/div to 59 mV/div  | ± 0.40 V                |
|  | 60 mV/div to 127 mV/div  | ± 0.86 V                |
|  | 128 mV/div to 279 mV/div   | ± 1.85 V                |
| 280 mV/div to 500 mV/div                 | ± 4.00 V   |                         |
| Offset accuracy <sup>1,2,3,*</sup>       | ± 2% of channel offset + 1% of full scale                            |                         |
| Offset accuracy (typical)                | ± 1% of channel offset + 1% of full scale                            |                         |
| Amplitude flatness <sup>4</sup>          | Any frequency ≤ 50 GHz:  |                         |
|  | < 0.3 dB within any 500 MHz span                                     |                         |
|  | < 0.5 dB within any 10 GHz span                                      |                         |
|  | Frequencies between 50 GHz and 90 GHz                                |                         |
| < 1 dB within any 10 GHz span            |  |                         |
| Frequencies between 90 GHz and 110 GHz   |  |                         |
| < 2 dB within any 10GHz span             |  |                         |
| Phase flatness <sup>5</sup>              | Any frequency ≤ 50 GHz:  |                         |
|  | < 1 degree within any 500 MHz span                                   |                         |
|  | < 2 degrees within any 10 GHz span                                   |                         |
|  | Frequencies between 50 GHz and 90 GHz                                |                         |
|  | < 3 degrees within any 10 GHz span                                   |                         |
|  | Frequencies between 90 GHz and 110 GHz                               |                         |
| < 7 degrees within any 10 GHz span       |  |                         |

1. Full scale is defined as 8 vertical divisions. Magnification is used below 7.5 mV/div. Below 7.5 mV/div, full scale is defined as 60 mV. The major scale settings are 1 mV/div, 2 mV/div, 5 mV/div, 10 mV/div, 20 mV/div, 50 mV/div, 100 mV/div, 200 mV/div and 500 mV/div. Magnification major scales of 1mV/div, 2mV/div & 5mV/div are not warranted for Offset Accuracy & DC Gain Accuracy.

2. Input impedance is valid when V/div scaling is adjusted to show all waveform vertical values within scope display.

3. Vertical resolution for 10 bits = 0.1% of full scale, for 14 bits = 0.006% of full scale.

4. Measured result using N2125A as reference. Maximum deviation from average in a span.

5. Measured result using N2125A as reference. Maximum deviation from best-fit line (degrees) in a span.

**\*Denotes warranted specifications, all others are typical. Valid after 30-minute warm up period and ± 5 °C from oscilloscope firmware calibration temperature**

# Vertical System – Performance Characteristics by Model - 3.5 mm Input Models

| Characteristic                       | UXR0104B  | UXR0134B | UXR0164B | UXR0204B | UXR0254B | UXR0334B |
|--------------------------------------|---|----------|----------|----------|----------|----------|
| Analog input connector               | Ruggedized 3.5 mm male - with AutoProbe II jack |          |          |          |          |          |
| Input impedance <sup>1</sup>         | 50 $\Omega$ , $\pm$ 3%                          |          |          |          |          |          |
| Input coupling                       | DC  |          |          |          |          |          |
| Full bandwidth analog input channels | 4   | 4        | 4        | 4        | 4        | 4        |
| Analog bandwidth (3 dB)              |   |          |          |          |          |          |
| Typical bandwidth                    | 10.5 GHz  | 13.6 GHz | 16.8 GHz | 21.0 GHz | 26.2 GHz | 33.0 GHz |
| Warranted bandwidth <sup>5</sup>     | 10.0 GHz  | 13.0 GHz | 16.0 GHz | 20.0 GHz | 25.0 GHz | 32.0 GHz |
| Rise time/fall time                  |   |          |          |          |          |          |
| 10 to 90% <sup>2</sup>               | 44.0 ps   | 33.8 ps  | 27.5 ps  | 22.0 ps  | 17.6 ps  | 13.3 ps  |
| 20 to 80% <sup>3</sup>               | 31.2 ps   | 23.9 ps  | 19.4 ps  | 15.6 ps  | 12.4 ps  | 9.4 ps   |
| ENOB typical <sup>4</sup>            |   |          |          |          |          |          |
| at $\geq 400$ mV <sub>fs</sub>       | 7.0   | 6.8      | 6.7      | 6.5      | 6.2      | 5.9      |
| at 40 mV <sub>fs</sub>               | 6.4   | 6.1      | 6.0      | 5.8      | 5.6      | 5.3      |

# Vertical System – Performance Characteristics by Model - 1.85 mm Input Models

| Characteristic                       | UXR0404B / UXR0402B                    | UXR0504B / UXR0502B | UXR0594B / UXR0592B | UXR0704B / UXR0702B |
|--------------------------------------|--|---------------------|---------------------|---------------------|
| Analog input connector               | 1.85 mm male - with AutoProbe III jack |                     |                     |                     |
| Input impedance <sup>1</sup>         | 50 $\Omega$ , $\pm$ 3%                 |                     |                     |                     |
| Input coupling                       | DC                                     |                     |                     |                     |
| Full bandwidth analog input channels | 4 / 2                                  | 4 / 2               | 4 / 2               | 4 / 2               |
| Analog bandwidth (3 dB)              |  |                     |                     |                     |
| Typical bandwidth                    | 42.0 GHz                               | 52.5 GHz            | 59.0 GHz            | 70.0 GHz            |
| Warranted bandwidth <sup>5</sup>     | 40.0 GHz                               | 50.0 GHz            | 59.0 GHz            | 67.0 GHz            |
| Rise time/fall time                  |  |                     |                     |                     |
| 10 to 90% <sup>2</sup>               | 11.0 ps                                | 8.8 ps              | 7.5 ps              | 6.3 ps              |
| 20 to 80% <sup>3</sup>               | 7.8 ps                                 | 6.2 ps              | 5.3 ps              | 4.4 ps              |
| ENOB typical <sup>4</sup>            |  |                     |                     |                     |
| at $\geq 400$ mV <sub>fs</sub>       | 5.8                                    | 5.6                 | 5.5                 | 5.4                 |
| at 60 mV <sub>fs</sub>               | 5.4                                    | 5.2                 | 5.1                 | 5.0                 |

1. Input impedance is valid when V/div scaling is adjusted to show all waveform vertical values within scope display.
2. Calculation based on  $Tr = 0.44/BW$ .
3. Calculation based on  $Tr = 0.31/BW$ .
4. The average value from DC to full bandwidth of model.
5. Denotes warranted specifications, all others are typical. Specifications are valid after 30-minute warm up period and  $\pm 5^\circ\text{C}$  from oscilloscope firmware calibration temperature.

# Vertical System – Performance Characteristics by Model - 1 mm Input AP Models

| Characteristic                       | UXR0051BP                                      | UXR0254BP /<br>UXR0252BP | UXR0404BP /<br>UXR0402BP | UXR0594BP /<br>UXR0592BP | UXR0704BP /<br>UXR0702BP |
|--------------------------------------|--|--------------------------|--------------------------|--------------------------|--------------------------|
| Analog input connector               | 1 mm ruggedized male - with AutoProbe III jack |                          |                          |                          |                          |
| Input impedance <sup>1</sup>         | 50 Ω, ± 3%                                     |                          |                          |                          |                          |
| Input coupling                       | DC   |                          |                          |                          |                          |
| Full bandwidth analog input channels | 1  | 4 / 2                    | 4 / 2                    | 4 / 2                    | 4 / 2                    |
| Analog bandwidth (3 dB)              |  |                          |                          |                          |                          |
| Typical bandwidth                    | 5.3 GHz  | 26.2 GHz                 | 42.0 GHz                 | 59.0 GHz                 | 73.5 GHz                 |
| Warranted bandwidth <sup>5</sup>     | 5.0 GHz  | 25.0 GHz                 | 40.0 GHz                 | 59.0 GHz                 | 67.0 GHz                 |
| Rise time/fall time                  |  |                          |                          |                          |                          |
| 10 to 90% <sup>2</sup>               | 88 ps  | 17.6 ps                  | 11.0 ps                  | 7.5 ps                   | 6.3 ps                   |
| 20 to 80% <sup>3</sup>               | 62 ps  | 12.4 ps                  | 7.8 ps                   | 5.3 ps                   | 4.4 ps                   |
| ENOB typical <sup>4</sup>            |  |                          |                          |                          |                          |
| at ≥ 400 mV <sub>fs</sub>            | 8.1  | 6.2                      | 5.8                      | 5.5                      | 5.4                      |
| at 60 mV <sub>fs</sub>               | 7.8  | 5.6                      | 5.4                      | 5.1                      | 5.0                      |

# Vertical System – Performance Characteristics by Model - 1 mm Input Models

| Characteristic                       | UXR0804B / UXR0802B                            | UXR1004B / UXR1002B | UXR1104B / UXR1102B |
|--------------------------------------|--|---------------------|---------------------|
| Analog input connector               | 1 mm ruggedized male - with AutoProbe III jack |                     |                     |
| Input impedance <sup>1</sup>         | 50 Ω, ± 3%                                     |                     |                     |
| Input coupling                       | DC   |                     |                     |
| Full bandwidth analog input channels | 4 / 2  | 4 / 2               | 4 / 2               |
| Analog bandwidth (3 dB)              |  |                     |                     |
| Typical bandwidth                    | 84.0 GHz                                       | 105.0 GHz           | 113.0 GHz           |
| Warranted bandwidth <sup>5</sup>     | 80.0 GHz                                       | 100.0 GHz           | 110.0 GHz           |
| Rise time/fall time                  |  |                     |                     |
| 10 to 90% <sup>2</sup>               | 5.5 ps   | 4.4 ps              | 4.0 ps              |
| 20 to 80% <sup>3</sup>               | 3.9 ps   | 3.1 ps              | 2.8 ps              |
| ENOB typical <sup>4</sup>            |  |                     |                     |
| at ≥ 400 mV <sub>fs</sub>            | 5.3  | 5.1                 | 5.0                 |
| at 60 mV <sub>fs</sub>               | 4.8  | 4.4                 | 4.2                 |

1. Input impedance is valid when V/div scaling is adjusted to show all waveform vertical values within scope display
2. Calculation based on  $T_r = 0.44/BW$
3. Calculation based on  $T_r = 0.31/BW$
4. The average value from DC to full bandwidth of model
5. Denotes warranted specifications, all others are typical. Specifications are valid after 30-minute warm up period and ± 5°C from oscilloscope firmware calibration temperature

# RMS Noise Floor – Performance Characteristics (Measured)

| RMS noise floor<br>vertical setting, full scale | UXR0104B                  | UXR0134B                  | UXR0164B                  | UXR0204B                  | UXR0254B                  | UXR0334B                  |
|---|---------------------------|---------------------------|---------------------------|---------------------------|---------------------------|---------------------------|
| 32 mV <sub>full scale</sub> (fs)                | 129 $\mu\text{V}_{(rms)}$ | 150 $\mu\text{V}_{(rms)}$ | 165 $\mu\text{V}_{(rms)}$ | 188 $\mu\text{V}_{(rms)}$ | 212 $\mu\text{V}_{(rms)}$ | 266 $\mu\text{V}_{(rms)}$ |
| 80 mV <sub>full scale</sub> (fs)                | 185 $\mu\text{V}_{(rms)}$ | 210 $\mu\text{V}_{(rms)}$ | 231 $\mu\text{V}_{(rms)}$ | 262 $\mu\text{V}_{(rms)}$ | 303 $\mu\text{V}_{(rms)}$ | 388 $\mu\text{V}_{(rms)}$ |
| 100 mV <sub>full scale</sub> (fs)               | 216 $\mu\text{V}_{(rms)}$ | 258 $\mu\text{V}_{(rms)}$ | 286 $\mu\text{V}_{(rms)}$ | 313 $\mu\text{V}_{(rms)}$ | 365 $\mu\text{V}_{(rms)}$ | 470 $\mu\text{V}_{(rms)}$ |
| 160 mV <sub>full scale</sub> (fs)               | 322 $\mu\text{V}_{(rms)}$ | 377 $\mu\text{V}_{(rms)}$ | 414 $\mu\text{V}_{(rms)}$ | 469 $\mu\text{V}_{(rms)}$ | 541 $\mu\text{V}_{(rms)}$ | 702 $\mu\text{V}_{(rms)}$ |
| 400 mV <sub>full scale</sub> (fs)               | 701 $\mu\text{V}_{(rms)}$ | 810 $\mu\text{V}_{(rms)}$ | 878 $\mu\text{V}_{(rms)}$ | 975 $\mu\text{V}_{(rms)}$ | 1.16 mV <sub>(rms)</sub>  | 1.48 mV <sub>(rms)</sub>  |
| 800 mV <sub>full scale</sub> (fs)               | 1.44 mV <sub>(rms)</sub>  | 1.58 mV <sub>(rms)</sub>  | 1.75 mV <sub>(rms)</sub>  | 1.92 mV <sub>(rms)</sub>  | 2.24 mV <sub>(rms)</sub>  | 2.91 mV <sub>(rms)</sub>  |
| 1.6 V <sub>full scale</sub> (fs)                | 2.97 mV <sub>(rms)</sub>  | 3.50 mV <sub>(rms)</sub>  | 3.77 mV <sub>(rms)</sub>  | 4.31 mV <sub>(rms)</sub>  | 4.97 mV <sub>(rms)</sub>  | 6.48 mV <sub>(rms)</sub>  |
| 4.0 V <sub>full scale</sub> (fs)                | 7.23 mV <sub>(rms)</sub>  | 7.86 mV <sub>(rms)</sub>  | 8.74 mV <sub>(rms)</sub>  | 9.61 mV <sub>(rms)</sub>  | 11.2 mV <sub>(rms)</sub>  | 14.7 mV <sub>(rms)</sub>  |
| 8.0 V <sub>full scale</sub> (fs)                | 14.1 mV <sub>(rms)</sub>  | 15.5 mV <sub>(rms)</sub>  | 17.2 mV <sub>(rms)</sub>  | 19.2 mV <sub>(rms)</sub>  | 22.3 mV <sub>(rms)</sub>  | 28.8 mV <sub>(rms)</sub>  |

| RMS noise floor<br>vertical setting, full scale | UXR0254BP /<br>UXR0252BP  | UXR0404B / UXR0402B<br>UXR0404BP / UXR0402BP | UXR0504B /<br>UXR0502B    | UXR0594B / UXR0592B<br>UXR0594BP / UXR0592BP |
|---|---------------------------|--|---------------------------|--|
| 60 mV <sub>full scale</sub> (fs)                | 290 $\mu\text{V}_{(rms)}$ | 340 $\mu\text{V}_{(rms)}$                    | 410 $\mu\text{V}_{(rms)}$ | 460 $\mu\text{V}_{(rms)}$                    |
| 100 mV <sub>full scale</sub> (fs)               | 400 $\mu\text{V}_{(rms)}$ | 490 $\mu\text{V}_{(rms)}$                    | 560 $\mu\text{V}_{(rms)}$ | 640 $\mu\text{V}_{(rms)}$                    |
| 160 mV <sub>full scale</sub> (fs)               | 570 $\mu\text{V}_{(rms)}$ | 720 $\mu\text{V}_{(rms)}$                    | 820 $\mu\text{V}_{(rms)}$ | 950 $\mu\text{V}_{(rms)}$                    |
| 400 mV <sub>full scale</sub> (fs)               | 1.3 mV <sub>(rms)</sub>   | 1.6 mV <sub>(rms)</sub>                      | 1.8 mV <sub>(rms)</sub>   | 2.1 mV <sub>(rms)</sub>                      |
| 800 mV <sub>full scale</sub> (fs)               | 2.6 mV <sub>(rms)</sub>   | 3.4 mV <sub>(rms)</sub>                      | 3.7 mV <sub>(rms)</sub>   | 4.3 mV <sub>(rms)</sub>                      |
| 1.6 V <sub>full scale</sub> (fs)                | 5.1 mV <sub>(rms)</sub>   | 6.7 mV <sub>(rms)</sub>                      | 7.5 mV <sub>(rms)</sub>   | 8.4 mV <sub>(rms)</sub>                      |
| 4.0 V <sub>full scale</sub> (fs)                | 13 mV <sub>(rms)</sub>    | 16 mV <sub>(rms)</sub>                       | 18 mV <sub>(rms)</sub>    | 20 mV <sub>(rms)</sub>                       |

| RMS noise floor<br>vertical setting, full scale | UXR0704B / UXR0702B<br>UXR0704BP / UXR0702BP | UXR0804B /<br>UXR0802B    | UXR1004B /<br>UXR1002B    | UXR1104B /<br>UXR1102B    | UXR0051BP                 |
|---|--|---------------------------|---------------------------|---------------------------|---------------------------|
| 60 mV <sub>full scale</sub> (fs)                | 500 $\mu\text{V}_{(rms)}$                    | 580 $\mu\text{V}_{(rms)}$ | 770 $\mu\text{V}_{(rms)}$ | 860 $\mu\text{V}_{(rms)}$ | 130 $\mu\text{V}_{(rms)}$ |
| 100 mV <sub>full scale</sub> (fs)               | 680 $\mu\text{V}_{(rms)}$                    | 780 $\mu\text{V}_{(rms)}$ | 990 $\mu\text{V}_{(rms)}$ | 1.1 mV <sub>(rms)</sub>   | 180 $\mu\text{V}_{(rms)}$ |
| 160 mV <sub>full scale</sub> (fs)               | 970 $\mu\text{V}_{(rms)}$                    | 1.1 mV <sub>(rms)</sub>   | 1.4 mV <sub>(rms)</sub>   | 1.5 mV <sub>(rms)</sub>   | 260 $\mu\text{V}_{(rms)}$ |
| 400 mV <sub>full scale</sub> (fs)               | 2.2 mV <sub>(rms)</sub>                      | 2.4 mV <sub>(rms)</sub>   | 2.8 mV <sub>(rms)</sub>   | 2.9 mV <sub>(rms)</sub>   | 580 $\mu\text{V}_{(rms)}$ |
| 800 mV <sub>full scale</sub> (fs)               | 4.5 mV <sub>(rms)</sub>                      | 4.8 mV <sub>(rms)</sub>   | 5.8 mV <sub>(rms)</sub>   | 6.1 mV <sub>(rms)</sub>   | 1.2 mV <sub>(rms)</sub>   |
| 1.6 V <sub>full scale</sub> (fs)                | 9.0 mV <sub>(rms)</sub>                      | 9.7 mV <sub>(rms)</sub>   | 12 mV <sub>(rms)</sub>    | 13 mV <sub>(rms)</sub>    | 2.3 mV <sub>(rms)</sub>   |
| 4.0 V <sub>full scale</sub> (fs)                | 21 mV <sub>(rms)</sub>                       | 23 mV <sub>(rms)</sub>    | 27 mV <sub>(rms)</sub>    | 29 mV <sub>(rms)</sub>    | 5.7 mV <sub>(rms)</sub>   |



# Vertical System – Performance Measurements – 1 mm & 1.85 mm Input Models

| Measurement                                   | Measured performance at 256 GSa/s  |                                     |                            |                                       |                                    |       |
|---|--|-------------------------------------|----------------------------|---------------------------------------|------------------------------------|-------|
| Banded ENOB                                   | 20 ns measurement by frequency span bandwidth @ center frequency (CF)  |                                     |                            |                                       |                                    |       |
|   | CF   | 113 GHz                             | 10 GHz                     | 5 GHz                                 | 2 GHz                              | 1 GHz |
|   | 67 GHz   | 5.0                                 | 7.6                        | 8.1                                   | 8.7                                | 9.0   |
|   | 90 GHz   | 4.8                                 | 7.5                        | 8.0                                   | 8.4                                | 8.7   |
|   | 110 GHz  | 4.9                                 | 6.9                        | 7.4                                   | 7.9                                | 8.2   |
| Displayed average noise level (DANL)          | 1 GHz wide span measured at Center Frequency (CF), 1 Hz reference:   |                                     |                            |                                       |                                    |       |
|   |  | 80 mV <sub>FS</sub> (-18 dBm range) |                            |                                       | 1.26 V <sub>FS</sub> (6 dBm range) |       |
|   | 1 GHz  | -161 dBm/Hz                         |                            |                                       | -138 dBm/Hz                        |       |
|   | 10 GHz   | -161 dBm/Hz                         |                            |                                       | -138 dBm/Hz                        |       |
|   | 25 GHz   | -159 dBm/Hz                         |                            |                                       | -137 dBm/Hz                        |       |
|   | 50 GHz   | -158 dBm/Hz                         |                            |                                       | -137 dBm/Hz                        |       |
|   | 75 GHz   | -158 dBm/Hz                         |                            |                                       | -138 dBm/Hz                        |       |
| 100 GHz                                       | -156 dBm/Hz  |                                     |                            | -136 dBm/Hz                           |                                    |       |
| Dynamic range<br>[2/3 * (TOI - DANL)]         | 6 dBm range, 200 mV/div @ 110 GHz BW<br>25 GHz CF, 100 MHz span, 1 Hz RBW  |                                     |                            | 103 dB                                |                                    |       |
| Signal to noise dynamic range                 | Measured with FFT: 0 dBm range, -1 dBm<br>signal, 100 MHz span, 1 KHz RBW, at +20<br>MHz from the center frequency (CF)  |                                     |                            | 1 GHz CF: 115 dB<br>67 GHz CF: 113 dB |                                    |       |
| Phase noise                                   | 1 GHz carrier, input signal 90% full scale   |                                     |                            |                                       |                                    |       |
|   |  | @ Offset                            | Single channel phase noise |                                       | 2 channel x-correlated             |       |
|   |  | 10 KHz                              | -120 dBc/Hz                |                                       | -121 dBc/Hz                        |       |
|   |  | 20 KHz                              | -124 dBc/Hz                |                                       | -127 dBc/Hz                        |       |
|   |  | 100 KHz                             | -137 dBc/Hz                |                                       | -147 dBc/Hz                        |       |
|   |  | 1 MHz                               | -143 dBc/Hz                |                                       | -151 dBc/Hz                        |       |
|   |  | 10 MHz                              | -143 dBc/Hz                |                                       | -156 dBc/Hz                        |       |
|   |  | 100 MHz                             | -142 dBc/Hz                |                                       | -158 dBc/Hz                        |       |
|   |  | 400 MHz                             | -141 dBc/Hz                |                                       | -165 dBc/Hz                        |       |
| Channel to channel phase /<br>phase coherency | Inter-channel jitter @ 39GHz, 1GHz BW:<br>± 2.5 deg (0.5 deg rms)  |                                     |                            |                                       |                                    |       |
| Two tone third-order intermodulation<br>(TOI) | 1.2 V <sub>is</sub> (6 dBm range), -12 dBm input/tone, 3 KHz RBW, 400 KHz span:<br>+22.9 dBm @ 3.65 GHz and 3.6501 GHz<br>+18.2 dBm @ 26.5 GHz and 26.5001 GHz |                                     |                            |                                       |                                    |       |

| Measurement   | Measured performance at 256 GSa/s   |                          |                          |
|---|---|--------------------------|--------------------------|
| 2 <sup>nd</sup> and 3 <sup>rd</sup> harmonic distortion | 60 mV <sub>FS</sub> (7.5 mV/div), -26 dBm input signal (~50% FS), 100 KHz RBW   |                          |                          |
|   | Fundamental   | 2 <sup>nd</sup> harmonic | 3 <sup>rd</sup> harmonic |
|   | 1 GHz   | ≤ -68 dBc                | ≤ -61 dBc                |
|   | 16.5 GHz  | ≤ -64 dBc                | ≤ -62 dBc                |
|   | 25 GHz  | ≤ -62 dBc                | ≤ -61 dBc                |
|   | 50 GHz  | ≤ -56 dBc                | ---                      |
|   | 700 mVFS (87.5 mV/div), -1 dBm input signal (~90% FS), 100 KHz RBW  |                          |                          |
|   | Fundamental   | 2 <sup>nd</sup> harmonic | 3 <sup>rd</sup> harmonic |
|   | 1 GHz   | ≤ -55 dBc                | ≤ -50 dBc                |
|   | 16.5 GHz  | ≤ -55 dBc                | ≤ -50 dBc                |
| 25 GHz  | ≤ -51 dBc   | ≤ -46 dBc                |                          |
| 50 GHz  | ≤ -44 dBc   | —                        |                          |
| Spurious-free dynamic range (SFDR)<br>(excl. harmonics) | Measured via FFT: 5 GHz center frequency, 10 GHz span, 100 kHz RBW, 0 dBm range, -1 dBm signal @ 700 mV FS (87.5 mV/div) with a 5 GHz input carrier   |                          | ≤ -65 dBc                |
|   | Measured via FFT: 50 GHz center frequency, 20 GHz span, 100 kHz RBW, 0 dBm range, -1 dBm signal @ 700 mV FS (87.5 mV/div) with a 50 GHz input carrier   |                          | ≤ -61 dBc                |
| Residuals, images, and spurious responses               | Signal related (non-harmonic, multiple per 16 GHz interval):<br>-52 dBc @ 0 dBm range<br>Residual responses (major per 16 GHz interval):<br>-65 dB <sub>FS</sub> @ 0 dBm range<br>-65 dBm clock spur @ 64 GHz |                          |                          |
| Error vector magnitude (EVM)                            | Two-channel bonded 802.11ay (61.56 GHz CF, 3.8 GHz span):   |                          | 1.23%                    |
|   | 5G NR, 1 CC (100 MHz), measured at 28 GHz:  |                          | 0.60%                    |
|   | 5G NR, 1 CC (100 MHz), measured at 39 GHz:  |                          | 0.90%                    |
| S11   | < 50 GHz, -15 dB    ≥ 50 GHz, -7 dB   |                          |                          |
| Conducted emissions                                     | Clock emissions conducted out front panel connector @ 64 GHz: -65 dBm   |                          |                          |

# Horizontal System – Performance Characteristics

| Characteristic  | Measured performance – All oscilloscope input connector types   |                                |
|---|---|--------------------------------|
| Main timebase range   | 2 ps/div to 20 s/div real-time (13 GHz to 33 GHz models)<br>1 ps/div to 20 s/div real-time (40 GHz to 110 GHz models)                       |                                |
| Main timebase delay range   | 200 s to -200 s real-time   |                                |
| Reference position  | Continuously adjustable across horizontal display range   |                                |
| Zoom timebase range   | 1 ps/div to current main timescale setting  |                                |
| Channel de-skew range   | ± 1 ms range, 10 fs resolution  |                                |
| Time scale accuracy* <sup>1</sup>                                       | ± (25 ppb initial + 100 ppb/year aging) first year of manufacture<br>± (25 ppb initial + 30 ppb/year aging) after first year of manufacture |                                |
| Intrinsic jitter <sup>3</sup> , acquired time range/delta-time interval | <b>Internal reference</b>   | <b>External reference</b>      |
| < 1 μs (100 ns/div)   | 15 fs rms   | 15 fs rms                      |
| 10 μs (1 μs/div)  | 25 fs rms   | 25 fs rms                      |
| 100 μs (10 μs/div)  | 40 fs rms   | 40 fs rms                      |
| 1 ms (100 μs/div)   | 50 fs rms   | 50 fs rms                      |
| Inter-channel intrinsic jitter <sup>2,3</sup>                           | < 10 fs rms   |                                |
| Inter-scope intrinsic jitter <sup>2,3</sup>                             | < 20 fs rms   |                                |
| Inter-channel skew <sup>2</sup>   | ± 2 ps pk   |                                |
| Inter-channel skew drift <sup>2,4</sup>                                 | ± 100 fs pk (256 GSa/s models)  | ± 150 fs pk (128 GSa/s models) |
| Inter-scope skew drift <sup>2,4</sup>                                   | ± 200 fs pk (256 GSa/s models)  | ± 250 fs pk (128 GSa/s models) |
| Measured time interval error (TIE)                                      | 400 mV <sub>FS</sub> , 70 GHz bandwidth, 90% input signal, 2.2 mV <sub>rms</sub> noise:37 fs rms@70 GHz                                     |                                |

\* Denotes warranted specification, all others are typical. Specs are valid after a 30-minute warm-up period and ± 5 °C from calibration temp.

1. initial = immediately after factory or user calibration.

2. intra-chan = both edges measured on same channel, inter-chan = two edges measured on different channels within the same scope chassis, inter-scope = two edges measured between channels across different scope chassis synchronized to the same time reference

3. Intrinsic Jitter is the time error of a single channel relative to an ideal time reference. External timebase reference values measured using a Wenzel 501-04608A 10 MHz reference. Intrinsic jitter value depends on acquisition time range for TIE formula and depends on delta-time between edges for all two-edge formulas.

4. Scope channels & signal interconnect de-skewed prior to measurement.

Skew between channels caused by ± 5 deg C temp change.

| Characteristic                                     | All oscilloscope input connector types   |
|--|--|
| Jitter measurement floor <sup>1,2</sup> (sec rms)  | $\sqrt{\left(\frac{\text{Noise floor}}{\text{Slew rate}}\right)^2 + (\text{Intrinsic jitter})^2}$  |
| Time interval error (sec rms)                      | $\sqrt{\left(\frac{\text{Noise floor}}{\text{Slew rate}}\right)^2 + (\text{Intrinsic jitter})^2}$  |
| Period jitter (sec rms)                            | $\sqrt{2} * \sqrt{\left(\frac{\text{Noise floor}}{\text{Slew rate}}\right)^2 + (\text{Intrinsic jitter})^2}$   |
| Cycle-cycle / N-cycle jitter (sec rms)             | $\sqrt{3} * \sqrt{\left(\frac{\text{Noise floor}}{\text{Slew rate}}\right)^2 + (\text{Intrinsic jitter})^2}$   |
| Inter-channel jitter <sup>2,4</sup> (sec rms)      | $\sqrt{\left(\text{Time interval error (Edge Chan1)}\right)^2 + \left(\text{Time interval error (Edge Chan2)}\right)^2 + \left(\text{Inter channel intrinsic jitter}\right)^2}$  |
| Inter-scope jitter <sup>2,4</sup> (sec rms)        | $\sqrt{\left(\text{Time interval error (Edge Scope1)}\right)^2 + \left(\text{Time interval error (Edge Scope2)}\right)^2 + \left(\text{Inter scope intrinsic jitter}\right)^2}$  |
| Delta-time measurement accuracy <sup>2,3,4,5</sup> |  |
| Intra-channel no averaging                         | $\pm \left[ 5 * \sqrt{\left(\text{Time interval error (Edge1)}\right)^2 + \left(\text{Time interval error (Edge2)}\right)^2} + \left(\left(\frac{\text{Time scale}}{\text{accuracy}}\right) * \text{Delta time}\right) \right]$  |
| Intra-channel 256 averages                         | $\pm \left[ \frac{5}{16} * \sqrt{\left(\text{Time interval error (Edge1)}\right)^2 + \left(\text{Time interval error (Edge2)}\right)^2} + \left(\left(\frac{\text{Time scale}}{\text{accuracy}}\right) * \text{Delta time}\right) \right]$   |
| Inter-channel no averaging                         | $\pm \left[ 5 * \sqrt{\left(\text{Time interval error (Edge1)}\right)^2 + \left(\text{Time interval error (Edge2)}\right)^2 + \left(\text{Inter channel intrinsic jitter}\right)^2} + \left(\left(\frac{\text{Time scale}}{\text{accuracy}}\right) * \text{Delta time}\right) + \left(\text{Inter channel skew drift}\right) \right]$            |
| Inter-channel 256 averages                         | $\pm \left[ \frac{5}{16} * \sqrt{\left(\text{Time interval error (Edge1)}\right)^2 + \left(\text{Time interval error (Edge2)}\right)^2 + \left(\text{Inter channel intrinsic jitter}\right)^2} + \left(\left(\frac{\text{Time scale}}{\text{accuracy}}\right) * \text{Delta time}\right) + \left(\text{Inter channel skew drift}\right) \right]$ |

1. Specifications are typical and valid after a 30-minute warm-up period and  $\pm 5$  °C from calibration temperature.
2. Scope channels and signal interconnect de-skewed prior to measurement.
3. Sample rate set to maximum. Noise and slew rate determined at fixed-voltage measurement threshold, near middle of signal. Displayed signal is not vertically clipped. Slew rate of sine wave = (peak signal amplitude)  $\cdot 2 \cdot \pi \cdot f$ , slew rate of fast step  $\approx 0.8 \cdot \text{amplitude} / (\text{risetime } 10\text{-}90\%)$ .
4. intra-chan = both edges on the same channel, inter-chan = two edges on different channels of the same scope chassis, inter-scope = two edges on different scope chassis. TIE(Edge1) = time-interval error measurement floor of first edge, TIE(Edge2) = time-interval error measurement floor of second edge.
5. Reading is the displayed DTMA measurement value. Do not double the listed TSA value in DTMA formula.

# DDC and Frequency Extension Option – Performance Characteristics

| DDC and frequency extension characteristic                   | Performance  |
|--|--|
| DDC center frequency resolution                              | Center frequency rounded to nearest 6.25 MHz interval  |
| DDC frequency range  | With frequency extension option: DC to 113 GHz (1 mm models)<br>DC to 70 GHz (1.85 mm models)<br>DC to 33 GHz (3.5 mm models)<br>Without frequency extension option: DC to max scope bandwidth |
| DDC sampling rate  | 50 MSa/s to 3,200 MSa/s (configurable in powers of two)  |
| Max DDC sampling rate  | Standard: 200 MSa/s<br>Opt 602: 3,200 MSa/s  |
| Max DDC signal analysis bandwidth ( $\pm 1$ dB)              | Standard: 160 MHz<br>Opt 602: 2.00 GHz<br>2.16 GHz $\pm 3$ dB (typical)  |
| DDC output   | 40 bits complex per sample (16 bits I/Q + flags and markers)   |
| 30 GHz BW frequency extension range (UXR0000-630)            | Min CF: 21 GHz<br>Max CF: 98 GHz (1 mm models)<br>55 GHz (1.85 mm models)<br>32 GHz (3.5 mm models)  |
| 20 GHz BW frequency extension range (UXR0000-620)            | Min CF: 14 GHz<br>Max CF: 103 GHz (1 mm models)<br>60 GHz (1.85 mm models)<br>23 GHz (3.5 mm models)   |
| 10 GHz BW frequency extension range (UXR0000-610)            | Min CF: 7 GHz<br>Max CF: 108 GHz (1 mm models)<br>65 GHz (1.85 mm models)<br>28 GHz (3.5 mm models)  |
| 5 GHz BW frequency extension range (UXR0000-605)             | Min CF: 3.5 GHz<br>Max CF: 110.5 GHz (1 mm models)<br>67.5 GHz (1.85 mm models)<br>30.5 GHz (3.5 mm models)  |
| 5 GHz BW frequency extension range up to 82GHz (UXR0000-682) | Min CF: 3.5 GHz<br>Max CF: 79.5 GHz (1 mm models)<br>67.5 GHz (1.85 mm models)<br>30.5 GHz (3.5 mm models)   |
| Frequency extension channel support                          | Center frequency configurable per channel, up to 4 channels  |

| DDC option/configuration                          | Bandwidth range    | Capture time @ max sample rate             |   |  |
|---|--------------------|--|---|--|
|   |                    | Std Mem<br>500 Mpts real<br>50 MSa complex | UXR0000-01G option<br>1 Gpt real<br>250 MSa complex | UXR0000-02G option<br>2 Gpts real<br>400 MSa complex |
| No DDC  | Up to 110 GHz      | 780 $\mu$ s                                | 3.9 ms  | 7.8 ms   |
| STD DDC<br>50 to 200 MSa/s complex                | 40 MHz to 160 MHz  | 625 ms                                     | 1.25 s  | 2 s  |
| UXR000-602/N2163A-602<br>50 to 3200 MSa/s complex | 40 MHz to 2.16 GHz | 15.6 ms                                    | 78 ms   | 125 ms   |

# Real Time Spectrum Analysis

## Real time spectrum analysis

|  |  |              |             |          |          |             |          |
|--|--|--------------|-------------|----------|----------|-------------|----------|
| Standard performance                                 | All Infiniium UXR-B Series come with a standard 160 MHz RTSA and DDC analysis bandwidth, with a frequency range up to the oscilloscope bandwidth, and all channels can have independent center frequency.<br>The specifications below apply to the paid options that unlock full RTSA performance. |              |             |          |          |             |          |
| Frequency range                                      | 0 Hz to oscilloscope bandwidth<br>With frequency extension option: <ul style="list-style-type: none"> <li>DC to 113 GHz (1 mm models)</li> <li>DC to 70 GHz (1.85 mm models)</li> <li>DC to 33 GHz (3.5 mm models)</li> </ul>  |              |             |          |          |             |          |
| Analysis bandwidth                                   | 40, 80, 160, or 320 MHz <sup>1</sup> . RTSA total Span is 320 MHz for simultaneously on all channels   |              |             |          |          |             |          |
| Per-channel control                                  | All channels use the same span, but can each be at different center frequencies. No data is stored; visualization only   |              |             |          |          |             |          |
| Performance data                                     | Typical passband magnitude flatness: +/- .25 dB from 160 MHz to max Frequency Range  |              |             |          |          |             |          |
| Minimum signal duration with 100% amplitude accuracy | 15 $\mu$ s   |              |             |          |          |             |          |
| Minimum detectable signal duration                   | 10 ns  |              |             |          |          |             |          |
| Available views                                      | Spectral density (color graded)  |              |             |          |          |             |          |
| Supported triggers                                   | Frequency mask trigger: must intersect, must not intersect, up to 8 zones (AND logic)  |              |             |          |          |             |          |
| Window types   | Rectangular, Hanning, Hamming, Blackman-Harris, Flattop  |              |             |          |          |             |          |
| Number of markers                                    | 200  |              |             |          |          |             |          |
| Supported marker types                               | Frequency, amplitude   |              |             |          |          |             |          |
| FFT rate, 100% POI                                   | Span   | FFT/s (RTSA) |             |          |          | POI (RTSA)  |          |
|  | 40 MHz   | 25,000       |             |          |          | 122 $\mu$ s |          |
|  | 80 MHz   | 50,000       |             |          |          | 62 $\mu$ s  |          |
|  | 160 MHz  | 100,000      |             |          |          | 30 $\mu$ s  |          |
|  | 320 MHz <sup>1</sup>   | 200,000      |             |          |          | 15 $\mu$ s  |          |
| Resolution bandwidth                                 |  |              | Window Type |          |          |             |          |
|  | Span   | Sample Rate  | Rectangle   | Hamming  | Hanning  | Blackman    | Flattop  |
|  | 40 MHz   | 50 MSa/s     | 12.2 KHz    | 16.7 KHz | 18.3 KHz | 24.5 KHz    | 46.6 KHz |
|  | 80 MHz   | 100 MSa/s    | 24.4 KHz    | 33.4 KHz | 36.6 KHz | 48.9 KHz    | 93.2KHz  |
|  | 160 MHz  | 200 MSa/s    | 48.8 KHz    | 66.8 KHz | 73.2 KHz | 97.8 KHz    | 186 KHz  |
| 320 MHz <sup>1</sup>                                 | 400 MSa/s  | 97.6 KHz     | 133 KHz     | 146 KHz  | 195 KHz  | 373 KHz     |          |

1. 320 MHz analysis bandwidth require option 602 and D9020WSAA

# Acquisition System – Performance Characteristics

| Acquisition characteristic   | 3.5 mm models   | 1.85 mm and 1 mm models                |
|--|---|--|
| Maximum real-time sample rate  | 128 GSa/s   | 256 GSa/s                              |
| Sampling resolution  | 7.8125 ps/Sample  | 3.90625 ps/Sample                      |
| Memory depth per channel<br>500 Mpts<br>1 Gpt<br>2 Gpts              | Standard<br>UXR0000-01G<br>UXR0000-02G  | Standard<br>UXR0000-01G<br>UXR0000-02G |
| Memory depth (with RT averaging)                                     | 320 Mpts  | 335.556 Mpts                           |
| Acquisition time at max sampling rate<br>500 Mpts<br>1 Gpt<br>2 Gpts | 3.9 ms<br>7.8 ms<br>15.6 ms   | 1.95 ms<br>3.9 ms<br>7.8 ms            |
| Sampling modes<br>Real-time  | Successive single shot acquisitions   |  |
| Real-time with averaging   | Selectable from 2 to 1,048,575  |  |
| Real-time and segmented <sup>1</sup> with peak detect                | 128 GSa/s   | 256 GSa/s                              |
| Real-time and segmented with high resolution                         | Real-time boxcar averaging reduces random noise and increases resolution  |  |
| Segmented memory   | Captures bursting signals at max sample rate without consuming memory during periods of inactivity  |  |
| Max # of segments  | Independent of memory option  |  |
| High-bandwidth trigger enabled                                       | 25,680  | 20,825                                 |
| High-bandwidth trigger disabled                                      | 134,885   | 134,885                                |
| Min time between triggers<br>High-bandwidth trigger enabled          | 5.0 $\mu$ s   |  |
| High-bandwidth trigger disabled                                      | 3.5 $\mu$ s   |  |
| Max time between triggers  | > 100,000 years   |  |
| Variable length segmented memory                                     | Captures bursting signals with variable lengths in DDC mode without consuming memory during periods of inactivity   |  |
| Max # of segments  | Dependent on memory depth, pulse width and DDC sample rate  |  |
| Min time between triggers  | Utilizes pre and post store buffering to enable gapless capture without deadtime (blind spots) between triggers   |  |
| Bandwidth filters  | Brick wall, 4 <sup>th</sup> order Bessel, Butterworth, bandpass<br>Raised Cosine & Butterworth response (clock > 100 GBd)   |  |
|  | > 285,700 waveforms per second (when in segment memory mode)<br>When in DDC Variable Length Segmented memory mode:  |  |
| Maximum update rate  | DDC sample rate   | Maximum segments <sup>1</sup>          |
|  | 400 MSa/s   | > 985k                                 |
|  | 800 MSa/s   | > 965k                                 |
|  | 1.6 GSa/s   | > 750k                                 |
|  | 3.2 GSa/s   | > 605k                                 |
| Filters<br>Bandwidth limit   | Brick wall, 4th order Bessel or Butterworth, selectable bandwidth value   |  |
| Frequency response   | Flat mag and linear phase, Gaussian mag and linear phase: slower filter roll off while maintaining linear phase   |  |
| Sin(x)/x interpolation   | On/off selectable FIR digital filter with selectable 2-32x ratio: digital signal processing adds points between acquired data points to enhance measurement accuracy & waveform display |  |

1. Segmented with peak detect extends acquisition time range by compressing un-aliased full-sample rate waveform samples into voltage range values collected over and reported at larger time intervals

# Trigger System – Performance Characteristics

| Hardware trigger                           |  |
|--|--|
| Trigger sources                            | All channel inputs, 1 auxiliary trigger input  |
| Sensitivity                                | 1 div p-p  |
| Edge trigger bandwidth                     | Equal to acquisition analog bandwidth  |
| Edge trigger bandwidth<br>(50 Ω AUX Input) | DC to 2 GHz @ 150 mV <sub>pp</sub><br>4 GHz @ 175 mV <sub>pp</sub><br>5 GHz @ ≥ 400 mV <sub>pp</sub>   |
| Minimum pulse width trigger                |  |
| Hardware                                   | 50 ps  |
| Software (InfiniiScan)                     | 40 ps  |
| Level range                                |  |
| Internal                                   | ± 4 div from center screen or ± 4 V, whichever is smaller  |
| Auxiliary                                  | ± 5 V (into 50 Ω), 5 V <sub>pp</sub> maximum input signal swing  |
| Sweep modes                                | Auto, triggered, single  |
| Display jitter (trigger jitter)            | 3.5mm models: 116 fs (rms) <sup>2</sup><br>1.85&1mm models: 71 fs (rms) <sup>3</sup>   |
| Trigger holdoff range                      | Fixed 40 ns to 10 s, random 100 ns to 10 s   |
| Trigger qualification<br>(AND qualifier)   | Qualify a trigger setup by logically ANDing or ORing it with signal levels on analog channels  |
| Trigger actions                            | Specify an action to occur (and the frequency of the action) when a trigger conditions occurs. Actions include email on trigger and execute "multipurpose" user setting.   |
| Trigger sequences                          | Sequence triggers let you trigger on an event that follows another event. Three stage trigger sequences including two-stage hardware (find event (A) and trigger event (B)) and one-stage InfiniiScan software trigger. Supports all hardware trigger modes except "edge then edge" and "video" and "Gbit serial." Supports "delay (by time)" and "reset (by time or event)" between two hardware sequences. |

1. Capturing 20ns pulse with 50ns pre and post store, with 02G memory option

2. Value shown is typical Display jitter for UXR0334B at 100 mV/div triggering on 500 mVpp 16 GHz sin wave signal.

3. Value shown is typical Display jitter for UXR1104B at 100 mV/div triggering on 500 mVpp 55 GHz sin wave signal.



### Trigger modes – hardware

|                        |   |
|------------------------|---|
| Burst                  | Trigger on the Nth edge of a burst that occurs after an idle time from 1.5 ns to 20 s.  |
| Edge                   | Triggers on a specified slope (rising, falling, or alternating between rising and falling) & voltage level on any channel or auxiliary trigger.   |
| Edge transition        | Trigger on rising or falling edges that cross two voltage levels in > or < the amount of time specified. Edge transition setting from 75 ps.  |
| Edge then edge (time)  | The trigger is qualified by an edge. After a specified time-delay between 1.5 ns to 20 s, a rising or falling edge on any one selected input will generate the trigger.   |
| Edge then edge (event) | The trigger is qualified by an edge. After a specified delay between 1 to 65,000,000,000 rising or falling edges, another rising or falling edge on any one selected input will generate the trigger.   |
| Glitch                 | Triggers on glitches narrower than the other pulses in your waveform by specifying a width less than your narrowest pulse and a polarity. Triggers on glitches as narrow as 50 ps.<br>Glitch range settings: < 75 ps to < 10 s.   |
| High-bandwidth         | Edge trigger up to scopes maximum bandwidth<br>(works with edge positive slope and edge negative slope only).   |
| OR'd edges             | Identifies a trigger condition by looking for selected edges on up to four channels.  |
| Pattern/state          | Identifies a trigger condition by looking for a specified pattern or a pattern and an edge (state) across the input channels.   |
| Pulse width            | Trigger on a pulse that is wider or narrower than other pulses in waveform by specifying a pulse width & a polarity. Triggers on pulse widths as narrow as 75 ps. Pulse width range settings 75 ps to 20 s. Trigger point can be configured for "end of pulse" or "time out".   |
| Window                 | Specify a voltage range and then trigger when the waveform either exits this range, enters this range, stays outside the range for too long or too short, or stays inside the range for too long or too short.<br>Range setting from 75 ps to 20 s.   |
| Runt                   | Trigger on a pulse that crosses one threshold but fails to cross a second threshold before crossing the first again. Can be time qualified with minimum setting of 75 ps.   |
| Timeout                | Triggers the oscilloscope when the waveform has been at a higher voltage than the voltage specified by the Level control for too long (High Too Long), when the waveform has been at a lower voltage than the Level voltage for too long (Low Too Long), or when the waveform has taken too long to pass through the Level voltage (Unchanged Too Long). Timeout settings from 75 ps to 20 s. |
| Setup and hold         | Trigger on violations of Setup time, Hold time, or both. Setup times from 75 ps to 20 s & hold times from 75 ps to 100 ns.  |
| Protocol               | Trigger on certain packets or patterns in protocol-based data.  |

**Trigger modes – software** (Requires D9020SCNA InfiniiScan event identification software)

|                    |  |
|--------------------|--|
| Zone qualify       | Software triggers on the user-defined zones on screen. Zones can be specified as either “must intersect” or “must not intersect.” Up to eight zones can be defined across multiple channels.   |
| Generic serial     | Software triggers on NRZ-encoded data up to 8.0 Gbps, up to 80-bit pattern. Support multiple clock data recovery methods including constant frequency, 1st-order PLL, 2nd-order PLL, explicit clock, explicit 1st-order PLL, explicit 2nd-order PLL, Fibre Channel, FlexRay receiver, FlexRay transmitter      |
| Measurement limit  | Software triggers on the results of the measurement values. For example, when the “pulse width” measurement is turned on, InfiniiScan measurement software trigger triggers on a glitch as narrow as 40 ps. When the “time interval error (TIE)” is measured, InfiniiScan can trigger on a specific TIE value. |
| Non-monotonic edge | Software triggers on the non-monotonic edge. The non-monotonic edge is specified by setting a hysteresis value.  |
| Runt               | Software triggers on a pulse that crosses one threshold but fails to cross a second threshold before crossing the first again. Unlike hardware runt trigger, InfiniiScan runt trigger can be further qualified via a hysteresis value.   |

## Measurements and Math

**Oscilloscope measurements**

|                         |   |
|-------------------------|---|
| Measurement update rate | > 50,000 measurement/sec (one measurement turned on)<br>> 250,000 measurement/sec/measurement (ten measurements turned on)  |
| Measurement modes       | Standard, measure all edges mode  |
| Statistics              | Displays the current, mean, minimum, maximum, range (max-min), standard deviation, number of measurements value for the displayed automatic measurements. Also shows Fail Min and Fail Max when measurement limit test is enabled |
| Level qualification     | Any channels that are not involved in a measurement can be used to level-qualify all timing measurements  |

**Waveform measurements**

|                  |  |
|------------------|--|
| Vertical         | V peak-peak, V min, V max, V upper, V middle, V lower, V overshoot, V preshoot, V time, peak-peak contrast, average, RMS, amplitude, base, top, overshoot, preshoot, crossing, pulse top, pulse base, pulse amplitude, area, optical mode amp (OMA), level mean, level RMS, level skew, level thickness, outer OMA |
| Time             | Delta time, rise time, fall time, positive width, negative width, burst width, burst period, burst interval, Tmin, Tmax, Tvolt, + pulse count, - pulse count   |
| Clock            | Period, frequency, duty cycle, phase, time interval error (TIE), cross-corelated TIE, N-period, period to period, positive width to positive width, neg width to neg width, duty cycle to duty cycle   |
| Data             | Time interval error (TIE), hold time, unit interval, N Unit Interval, unit interval to unit interval, noise, data rate, pattern length, CDR clock recovery rate, deemphasis, BER (cumulative), BER (per acq)   |
| Mixed            | Area, slew rate  |
| Frequency domain | FFT frequency, FFT magnitude, FFT delta frequency, FFT delta magnitude, FFT channel power, FFT power spectral density, FFT occupied bandwidth, peak detect mode, phase jitter <sup>1</sup>   |
| Eye-diagram      | Eye height, eye width, eye one level, eye zero level, eye jitter, eye skew, eye level, crossing percentage, Q factor, duty-cycle distortion, extension ratio (ER), outer ER, vertical eye closure (VEC)  |
| Optical          | Optical average power, optical mode amp (OMA), eye one level, eye zero level, extension ratio, outer OMA, outer ER   |

**Jitter analysis measurements – Requires D9020JITA EZJIT complete analysis application**

|             |  |
|-------------|--|
| Clock       | Time interval error, N-period, period to period, positive width to positive width, neg width to neg width, duty cycle to duty cycle          |
| Data        | Time interval error, noise, unit interval, N Unit Interval, unit interval to unit interval, data rate, clock recovery rate, CDR, de-emphasis |
| Phase noise | Phase jitter   |

**PAMn measurements – Requires D9020PAMA PAM4 analysis application**

|                          |   |
|--------------------------|---|
| PAMn measurements        | Level mean, level RMS, level skew, level thickness, eye height, eye width, eye skew, eye level, VEC, BER (Cumulative), BER (Per Acq), SER (Cumulative), SER (Per Acq), clock recovery rate, pattern length, rise time, fall time, and time interval error (TIE), composite histograms |
| Edge jitter measurements | PAM-4 12 Edge Jitter, J3U, J4U J5U, Jrms, J6U, and EOJ (PRBS9, PRBS13Q, PRBS31Q, PCIe Gen6 (52 symbols) and user defined pattern support up to PRBS23)  |
| PAM formats              | PAM-3, PAM-4, PAM-6, PAM-8, grey coded, uncoded   |

## Oscilloscope measurements (continued)

| Histograms                             |  |
|--|--|
| Source                                 | Waveform or measurement  |
| Orientation                            | Vertical (for timing and jitter measurements) or horizontal (noise and amplitude change) modes, regions are defined using waveform markers   |
| Measurements (available as a function) | Mean, standard deviation, mean $\pm$ 1, 2, and 3 sigma, median, mode, peak-to-peak, min, max, total hits, peak (area of most hits), X scale hits, X offset hits, full width at half maximum (FWHM), bin width  |
| Mask testing                           | Allows pass/fail testing to user-defined or Keysight-supplied waveform templates. Automask lets you create a mask template from a captured waveform and define a tolerance range in time/voltage or screen divisions. Test modes (run until) include test forever, test to specified time or event limit, and stop on failure. Executes "multipurpose" user setting on failure   |
| Waveform math                          |  |
| Number of functions                    | 16   |
| Hardware accelerated math operations   | Differential and common mode   |
| Math functions                         | Absolute value, add, amplitude demodulation (radar envelope), average, bus chart, Butterworth <sup>1</sup> , common mode, delay, differentiate, divide, envelope, FFT magnitude, FFT phase, FIR <sup>1</sup> , gating, high pass filter, histogram, InfiniiSim <sup>2</sup> (2 port, 4 port 1 src, 4 port CM, 4 port diff, 4 port src1, 4 port src2), horizontal gating, integrate, invert, LFE <sup>1</sup> , low pass filter (4th-order Bessel Thompson filter), magnify / duplicate, max, measurement trend, measurement log, min, multiply, pattern average, power, power efficiency, RT Eye <sup>1</sup> , smoothing, SqrtSumOfSquare <sup>1</sup> , square, square root, subtract, versus (XY), versus (XYZ qualified) and optional user defined function <sup>1</sup><br><sup>1</sup> Requires MATLAB® software option<br><sup>2</sup> Requires D9020ASIA software option |
| Fault Hunter                           |  |
| Auto Setup                             | 30 second statistical measurement analysis of incoming signal  |
| Result information                     | Test failure automatically saved in memory. Fault condition can be copied to trigger for further testing.  |
| Test results                           | Automatic identification of common digital signal errors: Positive glitch, negative glitch, slow rising edge, slow falling edge, positive runt, negative runt  |
| FFT                                    |  |
| Frequency range                        | DC to scope's maximum bandwidth  |
| Frequency resolution                   | Sample rate/memory depth = resolution  |
| Window modes                           | Hanning, flattop, rectangular, Blackman-Harris, Hamming  |
| Measurement modes                      |  |
| Automatic measurements                 | Measure menu access to all measurements, up to 20 measurements can be displayed simultaneously   |
| Multipurpose                           | Front-panel button activates up to ten pre-selected or up to ten user-defined automatic measurements   |
| Drag-and-drop measurement toolbar      | Measurement toolbar with common measurement icons that can be dragged and dropped onto the displayed waveforms   |
| Marker modes                           | Manual markers, track waveform data, track measurements, track RF (on FFT math function waveforms)   |
| Bookmarks and callouts                 | Supports callouts for measurements and FFT peaks. Supports bookmarks for team collaboration  |

# Platform Characteristics

## Computer system, peripherals and accessories

|                             |   |
|-----------------------------|---|
| Operating system            | Microsoft Windows 10 64-bit or newer Microsoft Windows release  |
| CPU                         | Intel i7-9700E octa-core CPU up to 4.4 GHz or higher performance CPU  |
| PC system memory            | 64 GB DDR4 RAM or higher capacity/performance RAM   |
| PC ports                    | USB 2.0 hi-speed (host), USB 2.0 hi-speed (device), VGA, DisplayPort, USB 3.0 (host), USB 3.0 (device), dual-monitor video output, 10/100/1000 LAN, LXI LAN   |
| Drives (SSD)                | 960GB Enterprise grade internal SSD removable hard drive or higher capacity/performance SSD   |
| Peripherals                 | Optical USB mouse, compact USB keyboard supplied. All UXR models support any Windows-compatible input device with a USB interface   |
| <b>File types</b>           |   |
| Waveforms                   | Compressed internal format (*.wfm (200 Mpts)), comma-separated values (*.csv (2 Gpts)), tab-separated values (*.tsv (2 Gpts)), public binary format (.bin (500 Mpts)), Y value files (*.txt (2 Gpts)), hierarchal data file (*.h5 (2 Gpts))   |
| Images                      | BMP, PNG, TIFF, GIF, JPG or osc file format   |
| <b>Included accessories</b> |   |
| All models                  | Country-specific power cord, front cover, open ended torque wrench (5/16 inch 8-in-lb), mini USB keyboard, USB optical mouse, and an ESD mat with wrist and heel straps   |
| 3.5 mm input models         | Qty (5) 3.5 mm Female-to-Female connector savers and (10) connector saver collars<br>Note: 10 GHz and 13 GHz models additionally include Qty (2) Precision BNC 50 $\Omega$ adaptors (N5442A)  |
| 1.85 mm input models        | One per channel (1.85 mm Female-to-Female connector savers), one 2.92 mm to 2.40 mm Female-to-Female coaxial adapter and one 3.5 mm Female-to-Female connector saver  |
| 1 mm input models           | One per channel (1 mm Female Ruggedized to 1 mm Female, and 1 mm Female Ruggedized to 1.85 mm Female connector savers), Qty (1) 1 mm Female Ruggedized to 2.92 mm Female connector saver, Qty (1) 3.5 mm Female-to-Female connector saver, and 1mm input specific open-ended torque wrenches (6 mm 4-in-lb, and 14 mm dual-ended: 4-in-lb & 10-in-lb)   |
| <b>I/O ports</b>            |   |
| Aux in                      | 5 V <sub>pp</sub> max signal between -5 V and +5 V, 50 $\Omega$ impedance   |
| Aux out                     | 0 V to 5 V, 50 $\Omega$ impedance   |
| Cal out                     | -2.4 V to +2.4 V, 50 $\Omega$ impedance   |
| Probe compensation terminal | 0 V to 5 V, 50 $\Omega$ impedance   |
| Reference clock input       | 400 MHz, 0.25 V <sub>pp</sub> to 0.50 V <sub>pp</sub> , 50 $\Omega$ impedance   |
| Reference clock output      | 400 MHz, 0.25 V <sub>pp</sub> to 0.50 V <sub>pp</sub> , 50 $\Omega$ impedance   |
| Sample clock input          | 8 GHz, -5 dBm to +15 dBm, 50 $\Omega$ impedance   |
| Sample clock output         | 8 GHz, +10 dBm to +15 dBm, 50 $\Omega$ impedance  |
| Timebase reference input    | Input frequency lock range: 10 MHz $\pm$ 20 ppm, 50 $\Omega$ impedance<br>Amplitude, sine wave input: 630 mV <sub>pp</sub> (0 dBm) min to 3.54 V <sub>pp</sub> (+15 dBm) max, 50 $\Omega$ impedance<br>Amplitude, square wave input: 500 mV <sub>pp</sub> min to 3.54 V <sub>pp</sub> max, 50 $\Omega$ impedance  |
| Timebase reference output   | Amplitude into 50 $\Omega$ (internal or external timebase reference selected):<br>1.1 to 2.0 V <sub>pp</sub> (+ 5 to + 10 dBm) sine wave<br>Frequency (internal timebase reference selected):<br>$\pm$ (25 ppb initial + 100 ppb/year aging) first year of manufacture<br>$\pm$ (25 ppb initial + 30 ppb/year aging) after first year of manufacture<br>Frequency, external timebase reference selected: external reference frequency |
| Trig out                    | 0 V to 5 V, 50 $\Omega$ impedance   |

**Display**

|                     |  |
|---------------------|--|
| Display             | 15.4-inch color XGA TFT-LCD with capacitive touch screen   |
| Intensity grayscale | 256-level intensity-graded display   |
| Resolution XGA      | 1024 pixels horizontally x 768 pixels vertically   |
| Annotation          | Up to 100 bookmarks can be inserted into the waveform window. Each can float or be tied to a specific waveform   |
| Grids               | Choose between 1-16 grids per waveform area, 10-bit vertical resolution  |
| Waveform areas      | Supports eight waveform areas plus chart mode for EZJIT, InfiniiSim, protocol, and PrecisionProbe  |
| Waveform styles     | Connected dots, dots, infinite persistence, color graded infinite persistence. Includes up to 256 levels of intensity-graded waveforms, variable persistence |

# General Characteristics

## General characteristics

|  |   |   |
|--|---|---|
| Temperature  | Operating: 5 to +40 °C up to 2,000 meters, de-rated between 2,000 and 3,000 meters by 1 °C for every 100 meters<br>Non-operating: -20 to +70 °C   |   |
| Humidity   | Operating: Up to 95% relative humidity (non-condensing) at +40 °C<br>Non-operating: Up to 90% relative humidity at +65 °C   |   |
| Altitude   | Operating: Up to 3,000 meters (9,842 feet); de-rate maximum temperature by 1 °C for every 100 meters above 2,000 meters<br>Non-operating: Up to 4,600 meters (15,090 feet)  |   |
| Vibration  | Operating random: 0.21 g (rms)<br>Non-operating random: 2.0 g (rms)<br>Swept sines: 0.50 g (rms)  |   |
| Power  | UXR0334B, UXR0254B, UXR0204B, UXR0164B, UXR0134B, UXR0104B  | 100 to 240 VAC at 50/60 Hz<br>Maximum input power 1350 VA   |
|  | UXR1102B, UXR1002B, UXR0802B, UXR0702B/BP, UXR0592B/BP, UXR0502B, UXR0402B/BP, UXR0252BP, UXR0051BP   | 110 to 240 VAC at 50/60 Hz<br>Maximum input power 1370 VA   |
|  | Well-regulated power is required for 110-120 V operation:<br>Connect only to a 20-amp outlet or a dedicated 15-amp outlet.  |   |
|  | UXR1104B, UXR1004B, UXR0804B, UXR0704B/BP, UXR0594B/BP, UXR0504B, UXR0404B/BP, UXR0254BP  | 200 to 240 VAC at 50/60 Hz<br>Maximum input power 2615 VA   |
| Connect only to outlets rated for 15 amps or higher. |   |   |
| Weight   | UXR0334B, UXR0254B, UXR0204B, UXR0164B, UXR0134B, UXR0104B  | 37.56 kg (82.8 lbs.)  |
|  | UXR1102B, UXR1002A, UXR0802B, UXR0702B/BP, UXR0592B/BP, UXR0502B, UXR0402B/BP, UXR0252BP, UXR0051BP   | 36.15 kg (79.7 lbs.)  |
|  | UXR1104B, UXR1004B, UXR0804B, UXR0704B/BP, UXR0594B/BP, UXR0504B, UXR0404B/BP, UXR0254BP  | 42.05 kg (92.7 lbs.)  |
| Dimensions   | Width: 435 mm with handles removed (17.126")<br>530 mm with handles (20.866")   |   |
|  | Depth: 513 mm main body (20.197")<br>560 mm including knobs and rear feet (22.047")   |   |
|  | Height: 311 mm (7U) with feet removed (12.244")<br>Installations with the optional N2156A rackmount kit will take up 8U to allow for airflow and cabling<br>333 mm with feet (13.11")   |   |
|  | Inputs:   | Connectors are 75 mm apart horizontally on the 4-channel frame and 150 mm apart on the 2-channel frame.                     |
|  | Centers are:  | 49 mm above the surface when resting flat (no tilt levers) and<br>90 mm above the surface when using the front tilt levers. |
| Clearances:  | Fans draw cool air in from the sides and bottom and blows it out the back of the oscilloscope.<br>Allow at least 8 inches (203 mm) of clearance from the rear.<br>Side handles provide sufficient airflow clearance side to side. |   |
| Safety   | CAN/CSA-C22.2 No. 61010-1-12<br>ANSI/UL Std. No. 61010-1:2018   |   |

# Definitions

## **Measured (meas)**

An attribute measured during development for purposes of communicating the expected performance. This data is not warranted, does not include measurement uncertainty, and is measured at room temperature (approximately 23°C).

## **Nominal (nom)**

The mean or average characteristic performance, or the value of an attribute that is determined by design such as a connector type, physical dimension, or operating speed. This data is not warranted and is measured at room temperature (approximately 23°C).

## **Specification (spec)**

The warranted performance of a calibrated instrument that has been stored for a minimum of 2 hours within the operating temperature range of 5 – 40°C and after a 30-minute warm up period.

## **Typical (typ)**

The characteristic performance, which 80% or more of manufactured instruments will meet. This data is not warranted, does not include measurement uncertainty, and is valid only at room temperature (approximately 23°C).

## **Operating frequency range**

The operating frequency range is the frequency range of corrected signal spectral components by deembedding for frequency and phase characteristics of the individual hardware.

## **Analog bandwidth**

The analog bandwidth describes the 3 dB bandwidth of the full opto-electronic input path without any frequency or phase corrections.

## **Sensitivity**

The sensitivity limit corresponds to the received signal power at the input interface for which a 32 GBaud DP-QPSK exhibits an EVM of 32.5% or less. An EVM of 32.5% corresponds to a BER of 1E-3 for assumed added Gaussian white noise (AWGN) according to  $=0.5 \cdot \text{ERFC}(1/(\text{SQRT}(2) \cdot (\text{EVM}^2 + 1)))$ .

## **Effective Number of Bits (ENOB)**

Definition in accordance with IEEE 1057: "For an input sinewave of specified frequency and amplitude, ENOB is the number of bits of an ideal waveform recorder for which the rms quantization error is equal to the rms NAD of the waveform recorder under test." ENOB is determined by equation.

# Confidently Covered by Keysight Services

Prevent delays caused by technical questions, or system downtimes due to instrument maintenance and repairs with Keysight Services. Keysight Services are here to support your test needs with expert technical support, instrument repair and calibration, software support, training, alternative acquisition program options, and more.

A KeysightCare agreement provides dedicated, proactive support through a single point of contact for instruments, software, and solutions. KeysightCare covers an extensive group of instruments, application software, and solutions and ensures optimal uptime, faster response, faster access to experts, and faster resolution.

## Keysight Services

| Offering                                   | Benefits   |
|--|--|
| KeysightCare                               | KeysightCare provides elevated support for Keysight instruments and software, with access to technical support experts that respond within a specified time and ensure committed repair and calibration turnaround times (TAT). KeysightCare offers multiple service agreement tiers, including KeysightCare Assured, Enhanced, and Application Software Support. See the <a href="#">KeysightCare data sheet</a> for details. |
| KeysightCare Assured                       | KeysightCare Assured goes beyond basic warranty with repair services that include committed TAT and unlimited access to technical experts.   |
| KeysightCare Enhanced                      | KeysightCare Enhanced includes all the benefits of KeysightCare Assured plus Keysight’s accurate and reliable calibration services, accelerated, and committed TAT, and technical response.  |
| Keysight Support Portal & Knowledge Center | All KeysightCare tiers include access to the Keysight Support Portal where you can manage support and service resources related to your assets such as service requests, and status, or browse the Knowledge Center.   |
| Education Services                         | Build confidence and gain new skills to make accurate measurements, with flexible Education Services developed by Keysight experts. Including Start-up Assistance.   |
| Alternative acquisition options            |  |
| KeysightAccess                             | Reduce budget challenges with a subscription service enabling you to get the instruments, software, and technical support you want for your test needs.  |



## Recommended services

Maximize your test system up-time by securing technical support, repair, and calibration services with committed response and turnaround times. 1-year KeysightCare Assured is included in every new instrument purchase. Obtain multi-year KeysightCare upfront to eliminate the need for lengthy and tedious paperwork and yearly requests for maintenance budget. Plus, you benefit from secured service for 2, 3, or 5 years.

| Service                       | Function   |
|-------------------------------|--|
| <b>KeysightCare Enhanced*</b> | <b>Includes Tech Support, Warranty and Calibration</b>       |
| R-55B-001-1                   | KeysightCare Enhanced – Upgrade 1 year                       |
| R-55B-001-2                   | KeysightCare Enhanced – Extend to 2 years                    |
| R-55B-001-3                   | KeysightCare Enhanced – Extend to 3 years (Recommended)      |
| R-55B-001-5                   | KeysightCare Enhanced – Extend to 5 years (Recommended)      |
| <b>KeysightCare Assured</b>   | <b>Includes Tech Support and Warranty</b>                    |
| R-55A-001-2                   | KeysightCare Assured – Extend to 2 years                     |
| R-55A-001-3                   | KeysightCare Assured – Extend to 3 years                     |
| R-55A-001-5                   | KeysightCare Assured – Extend to 5 years                     |
| <b>Start-Up Assistance</b>    |  |
| PS-S10                        | Included – instrument fundamentals and operations starter    |
| PS-S20                        | Optional, technology & measurement science standard learning |

\* Available in select countries. For details, please view the datasheet. R-55B-001-2/3/5 must be ordered with R-55B-001-1.

## More Information

Thank you for choosing a Keysight UXR-Series Oscilloscope. Keysight Infiniium UXR-Series oscilloscopes set a new standard for real-time oscilloscope accuracy, performance and upgradability, with models ranging from 5 GHz to 110 GHz. Proven industry best signal integrity, 10-bits of vertical resolution and ultra-low noise floor specifications allow for the truest representation of signals. Invest with confidence today, knowing you have the ability to meet the needs and technology advancements of tomorrow. For more information on the Keysight Infiniium UXR-Series, check out the following:

- [UXR Technical Overview](#)
- [UXR Configuration Guide](#)

Keysight enables innovators to push the boundaries of engineering by quickly solving design, emulation, and test challenges to create the best product experiences. Start your innovation journey at [www.keysight.com](http://www.keysight.com).



This information is subject to change without notice. © Keysight Technologies, 2023, Published in USA, July 25, 2023, 3123-1313.EN